

Safety Precautions



Sub LCD

Your phone has an external LCD screen on the folder. When the folder is closed, it indicates that you have an incoming call or message. It also alerts you when you have set an alarm at the specified time by flashing its backlight and showing the corresponding icon on it.

Standby is the most basic state of your phone. The phone goes into

Use the Key Lock feature to make sure that the keys are not pressed accidentally, such as when the phone slips around inside a briefcase.

In Standby Mode, press and hold the key. “Key Locked” appears on the display and the keys are immediately locked.

To view the various functions/options available and select the one required :

1 Press the appropriate soft key.

2 To Press the

Select the: soft key or the

-

¥

To clear

The last digit displayed

Any other digit in the number

Press

The soft key

The or key until the cursor is to the right of the digit to be cleared. Press

When someone calls you, the phone alerts you by ringing, blinking the color LED and displaying the call alert screen.

If you are subscribed to the Caller Line Identification service and the caller can be identified, the caller's phone number or name and image if stored in your Phonebook, displays. Contact your service provider for availability.

You can reject the call by pressing and holding the volume keys before opening the folder.

1 If the *Answer Mode* menu (*Menu 4-3-4*) is set to *Any Key*, open the folder or press any key except the **key** and the **soft key** to answer the call.

If the menu is set to *Send Key*, you must press the **key** or the **soft key** to answer the call.

To reject the call, press the **key** or the **soft key**.

2 You may end the call by closing the folder or pressing the **key**.

1 Press the **soft key** to enter In-call Options.

2 Press the **or** key to scroll to *Mute Off*.

3 Press the **soft key**.

Your phone receives an incoming message during a call. You can read it immediately without disconnecting the call. You can also send a message during a call.

1 During a call, press the **Message** soft key.

2 Select the *Message* option and press the **Message** soft key.

The phone enters the *Message* menu. For details about using the message service, see page 59.

1 During a call, press the **Message** soft key.

2 Press the **Left** or **Right** key to scroll to *DTMF On*.

Entering Text

Entering Text






1 Access the *Message* menu, scroll to *Voice Mail* and press the soft key.

2 Select *Call Voice Mail* to automatically dial the voice center number.

When the center answers, follow the voice prompts to listen to the message.

Note : When you use this feature, if the Voice Mail center number is not currently stored in your phone, the phone alerts you that the center number is not stored and asks you to enter the number now. To enter the number, press the soft key and enter the number.

For further details about the Voice mMil feature, please contact your service provider.

- 1** With the *Received No.* option selected, press the  soft key.
The Received Number list displays.
- 2** Press the  or  key to scroll to the number you want to view on the list.
- 3** When the number displays, press the  key to dial the number.
Press the  soft key for the following options.

3 Select **Set Divert** and select to either divert to the Voice Mail or if to an alternative number. Enter the number to which the calls are to be diverted and press the **soft key**.

To enter an international code, press the **0** key until the **+** sign displays.

4 The phone sends your settings to the network and the network's acknowledgement displays.

You can deactivate all call diverting settings by selecting the **Cancel**

All the only way to be able to use the 3rd key n0.06 413.1 515 -413.04 reW n3..39303.0555 -41 0 0 20.39 28.74 201.0 0 situT/F1er en0 0 wan3

4 Press the **key to move to the next field.**

4 Phone Number fields and 1 E-mail field are available.







Press the **key** to activate the field.

Press the **key** to delete the number one by one and
press the **soft key** to save.

Press the **key** to go to the next Phone Number field.

- 1 In Standby Mode, press the [] soft key.**
The PHONEBOOK options display.

You can schedule up to 50 events for one day.

- 1** Highlight a date on the calendar referring to “Scrolling through the Calendar” above.
- 2** Press the  soft key to access the Scheduler options.
- 3** Press the  or  key to highlight Make and press the  soft key.
- 4** Press the  or  key to select

You can find an event using its date, type and note.

- 1** On the calendar, press the **Go to Date** soft key.
- 2** Press the **Left** or **Right** key to select *Go to Date* and press the **Enter** soft key.
- 3** Enter the period using the number keypad.
You can move the cursor through the date input fields by using the navigation keys.
- 4** Enter the first few letters of the note and press **Enter**.

- 1 Highlight a date on the calendar, referring to “Scrolling through the Calendar” on page 115.
- 2 Press the soft key to access the Scheduler options. Select Daily view, select the Options soft key, scroll down and select Delete, Delete Event or Delete Day.

1 On the calendar, press the soft key to access the Scheduler options.

Your phone comes equipped with a WAP (Wireless Application Protocol)

● ● ● Note : To access the startup homepage from any other screen in the WAP Browser, use the key.

Glossary

